

ZA Series

Amplifier



ZA-120 (Front)



ZA-120 (Back)

Introduction of Features:

The mixer amplifier have power ratings 120w. They are featured of one microphone inputs, one aux input and one aux output.

Individual gain controls are provided for Mp3, Bluetooth, AUX, MIC, Treble and Bass controls. 70V, 100V and low impedance 4-16 ohms speaker outputs are provided.

Extensive protection from short-circuit, overload and high temp.

Features

Built-in MP3 player and FM tuner and remote control.

MP3 Player with USB, Bluetooth, SD port and fluorescent screen to display the sound number and sound name.

Four function buttons: previous, play/stop, next and mode.

70V, 100V and low impedance 4-16 ohms speaker output.

One Mic input by phone jack type.

Mic volume controls and bass/treble tone control.

High temp, overload and short-circuit protection.

Specifications

Rated Power Output: 120W

Speaker outputs: 70V, 100V and low impedance 4-16 ohms

Input Sensitivity & Impedance : Mic -55dB/600Ω, Unbalanced phone jack input

Aux -14dB/10KΩ, Unbalanced RCA input.

Tone: Bass: ±10dB at 100Hz

Treble: ±10dB at 10KHz

Frequency Response: 40Hz-18KHz(±3dB)

S/N Ratio : MIC: >70dB, AUX : >76dB

THD: Less than 0.2% at the 1KHz

MP3 Support Format: MP3, WMA

Maximum Support Capacity: 16GB USB drive

Power Supply: ~110V/60Hz or ~230V/50Hz

Dimensions: 315 x 270 x 120mm

Color:Black

