



ZM-S100

Smart Digital Multimeter



**4000 Counts
Smart Multimeter**

Standard Accessories

1. 2 x Battery
2. 2 x Test lead
3. 1 x Standard user manual

Specifications	Range	Accuracy
DC Voltage	4.000V/40.00V/400.0V/600V	±(0.5%+3)
AC Voltage	4.000V/40.00V/400.0V/600V	±(1.0%+3)
DC Current	999.9mA	±(1.0%+4)
	9.999A	±(1.0%+4)
AC Current	999.9mA	±(2.0%+3)
	9.999A	±(2.0%+3)
Resistance	4.000kΩ	±(1.5%+3)
	40.00kΩ/400.0kΩ/4.000MΩ	±(0.5%+3)
	40.00MΩ	±(1.5%+3)
Continuity	●	
NCV	●	

Features

Auto ranging	True RMS	Data hold
Backlight/Flashlight	Low battery alert	Auto power off
Smart mode		

General

Power Supply	2 x 1.5V AAA Battery
Dimension	120x61x28mm
Weight	117g